

## Batteries for Cars

|             | Performance   |         | Dimensions |        |        |        | Technical characteristics |          |               |
|-------------|---------------|---------|------------|--------|--------|--------|---------------------------|----------|---------------|
| Part number | Capacity (Ah) | CCA (A) | Box size   | L (mm) | W (mm) | H (mm) | Hold Down                 | Polarity | Terminal Type |

### FULMEN AGM

|        |     |     |     |     |     |     |     |       |                |
|--------|-----|-----|-----|-----|-----|-----|-----|-------|----------------|
| FK454  | 45  | 380 | B24 | 237 | 127 | 227 | B0  | ETN 0 | EN taper post  |
| FK457  | 45  | 380 | B24 | 237 | 127 | 227 | B0  | ETN 1 | JIS taper post |
| FK508  | 50  | 800 | G34 | 260 | 173 | 206 | B7  | ETN 9 | EN taper post  |
| FK600  | 60  | 680 | L02 | 242 | 175 | 190 | B13 | ETN 0 | EN taper post  |
| FK620  | 62  | 680 | L02 | 242 | 175 | 190 | B13 | ETN 0 | EN taper post  |
| FK700  | 70  | 760 | L03 | 278 | 175 | 190 | B13 | ETN 0 | EN taper post  |
| FK720  | 72  | 760 | L03 | 278 | 175 | 190 | B13 | ETN 0 | EN taper post  |
| FK800  | 80  | 800 | L04 | 315 | 175 | 190 | B13 | ETN 0 | EN taper post  |
| FK820  | 82  | 800 | L04 | 315 | 175 | 190 | B13 | ETN 0 | EN taper post  |
| FK950  | 95  | 850 | L05 | 353 | 175 | 190 | B13 | ETN 0 | EN taper post  |
| FK960  | 96  | 850 | L05 | 353 | 175 | 190 | B13 | ETN 0 | EN taper post  |
| FK1050 | 105 | 950 | L06 | 392 | 175 | 190 | B13 | ETN 0 | EN taper post  |
| FK1060 | 106 | 950 | L06 | 392 | 175 | 190 | B13 | ETN 0 | EN taper post  |

### FULMEN EFB

|        |     |     |     |     |     |     |           |       |               |
|--------|-----|-----|-----|-----|-----|-----|-----------|-------|---------------|
| FL550  | 55  | 540 | L01 | 207 | 175 | 190 | B13       | ETN 0 | EN taper post |
| FL600  | 60  | 640 | L02 | 242 | 175 | 190 | B13       | ETN 0 | EN taper post |
| FL604  | 60  | 520 | D23 | 230 | 173 | 222 | B0        | ETN 0 | EN taper post |
| FL605  | 60  | 520 | D23 | 230 | 173 | 222 | B0        | ETN 1 | EN taper post |
| FL652  | 65  | 650 | LB3 | 278 | 175 | 175 | B13       | ETN 0 | EN taper post |
| FL700  | 70  | 760 | L03 | 278 | 175 | 190 | B13       | ETN 0 | EN taper post |
| FL752  | 75  | 730 | LB4 | 315 | 175 | 175 | B13       | ETN 0 | EN taper post |
| FL754  | 75  | 750 | D26 | 260 | 173 | 222 | B0        | ETN 0 | EN taper post |
| FL800  | 80  | 800 | L04 | 315 | 175 | 190 | B13       | ETN 0 | EN taper post |
| FL955  | 95  | 800 | D31 | 306 | 173 | 222 | Korean B1 | ETN 1 | EN taper post |
| FL954  | 95  | 800 | D31 | 306 | 173 | 222 | Korean B1 | ETN 0 | EN taper post |
| FL1000 | 100 | 900 | L05 | 353 | 175 | 190 | B13       | ETN 0 | EN taper post |
| FL1050 | 105 | 950 | L06 | 392 | 175 | 190 | B13       | ETN 0 | EN taper post |

|             | Performance   |         | Dimensions |        |        |        | Technical characteristics |          |               |
|-------------|---------------|---------|------------|--------|--------|--------|---------------------------|----------|---------------|
| Part number | Capacity (Ah) | CCA (A) | Box size   | L (mm) | W (mm) | H (mm) | Hold Down                 | Polarity | Terminal Type |

## FULMEN Start-Stop Auxiliary

|       |    |     |     |     |     |     |    |       |                        |
|-------|----|-----|-----|-----|-----|-----|----|-------|------------------------|
| FK091 | 9  | 120 | C54 | 150 | 90  | 105 | B0 | ETN 1 | M12                    |
| FK111 | 11 | 150 | C55 | 150 | 90  | 130 | B0 | ETN 1 | M04                    |
| FK131 | 13 | 200 | C56 | 150 | 90  | 145 | B0 | ETN 1 | M04                    |
| FK143 | 14 | 80  | C76 | 150 | 100 | 100 | B0 | ETN 3 | Screwed/Lug            |
| FK151 | 15 | 200 | C56 | 150 | 90  | 145 | B0 | ETN 1 | Small taper post (JLR) |

## FULMEN Formula Xtreme

|        |     |     |     |     |     |     |              |       |                |
|--------|-----|-----|-----|-----|-----|-----|--------------|-------|----------------|
| FA406  | 40  | 350 | B19 | 187 | 127 | 220 | B1           | ETN 0 | JIS taper post |
| FA456  | 45  | 390 | B24 | 237 | 127 | 227 | B1           | ETN 0 | JIS taper post |
| FA472  | 47  | 450 | LB1 | 207 | 175 | 175 | B13          | ETN 0 | EN taper post  |
| FA530  | 53  | 540 | L01 | 207 | 175 | 190 | B13          | ETN 0 | EN taper post  |
| FA601  | 60  | 600 | L02 | 242 | 175 | 190 | B13          | ETN 1 | EN taper post  |
| FA612  | 61  | 600 | LB2 | 242 | 175 | 175 | B13          | ETN 0 | EN taper post  |
| FA640  | 64  | 640 | L02 | 242 | 175 | 190 | B13          | ETN 0 | EN taper post  |
| FA654  | 65  | 580 | D23 | 230 | 173 | 222 | Korean B1    | ETN 0 | EN taper post  |
| FA722  | 72  | 720 | LB3 | 278 | 175 | 175 | B13          | ETN 0 | EN taper post  |
| FA754  | 75  | 630 | D26 | 270 | 173 | 222 | Korean B1+B6 | ETN 0 | EN taper post  |
| FA755  | 75  | 630 | D26 | 270 | 173 | 222 | Korean B1+B6 | ETN 1 | EN taper post  |
| FA770  | 77  | 760 | L03 | 278 | 175 | 190 | B13          | ETN 0 | EN taper post  |
| FA852  | 85  | 800 | LB4 | 315 | 175 | 175 | B13          | ETN 0 | EN taper post  |
| FA900  | 90  | 720 | L04 | 315 | 175 | 190 | B13          | ETN 0 | EN taper post  |
| FA954  | 95  | 800 | D31 | 306 | 173 | 222 | Korean B1    | ETN 0 | EN taper post  |
| FA955  | 95  | 800 | D31 | 306 | 173 | 222 | Korean B1    | ETN 1 | EN taper post  |
| FA1000 | 100 | 900 | L05 | 353 | 175 | 190 | B13          | ETN 0 | EN taper post  |
| FA1050 | 105 | 850 | LH4 | 315 | 175 | 205 | B13          | ETN 0 | EN taper post  |

## FULMEN Formula

|        |    |     |     |     |     |     |                |       |                |
|--------|----|-----|-----|-----|-----|-----|----------------|-------|----------------|
| FB356  | 35 | 240 | B19 | 187 | 127 | 220 | B0             | ETN 0 | JIS taper post |
| FB356A | 35 | 240 | B19 | 187 | 127 | 220 | Korean B1 Long | ETN 0 | JIS taper post |
| FB357  | 35 | 240 | B19 | 187 | 127 | 220 | B0             | ETN 1 | JIS taper post |
| FB440  | 44 | 400 | L00 | 175 | 175 | 190 | B13            | ETN 0 | EN taper post  |
| FB442  | 44 | 420 | LB1 | 207 | 175 | 175 | B13            | ETN 0 | EN taper post  |
| FB457  | 45 | 330 | B24 | 237 | 127 | 227 | B0             | ETN 1 | JIS taper post |

|             | Performance   |         | Dimensions |        |        |        | Technical characteristics |          |                          |
|-------------|---------------|---------|------------|--------|--------|--------|---------------------------|----------|--------------------------|
| Part number | Capacity (Ah) | CCA (A) | Box size   | L (mm) | W (mm) | H (mm) | Hold Down                 | Polarity | Terminal Type            |
| FB450       | 45            | 330     | E02        | 220    | 135    | 225    | B1                        | ETN 0    | EN taper post            |
| FB451       | 45            | 330     | E02        | 220    | 135    | 225    | B1                        | ETN 1    | EN taper post            |
| FB454       | 45            | 330     | B24        | 237    | 127    | 227    | B0                        | ETN 0    | EN taper post            |
| FB455       | 45            | 330     | B24        | 237    | 127    | 227    | B0                        | ETN 1    | EN taper post            |
| FB456       | 45            | 330     | B24        | 237    | 127    | 227    | B0                        | ETN 0    | JIS taper post           |
| FB500       | 50            | 450     | L01        | 207    | 175    | 190    | B13                       | ETN 0    | EN taper post            |
| FB501       | 50            | 450     | L01        | 207    | 175    | 190    | B13                       | ETN 1    | EN taper post            |
| FB504       | 50            | 360     | D20        | 200    | 173    | 222    | Korean B1                 | ETN 0    | EN taper post            |
| FB558       | 55            | 620     | G75        | 230    | 180    | 186    | B7                        | ETN 1    | SAE S 3/8" side Terminal |
| FB602       | 60            | 540     | LB2        | 242    | 175    | 175    | B13                       | ETN 0    | EN taper post            |
| FB604       | 60            | 480     | D23        | 230    | 173    | 222    | Korean B1                 | ETN 0    | EN taper post            |
| FB605       | 60            | 480     | D23        | 230    | 173    | 222    | Korean B1                 | ETN 1    | EN taper post            |
| FB620       | 62            | 540     | L02        | 242    | 175    | 190    | B13                       | ETN 0    | EN taper post            |
| FB621       | 62            | 540     | L02        | 242    | 175    | 190    | B13                       | ETN 1    | EN taper post            |
| FB704       | 70            | 540     | D26        | 270    | 173    | 222    | Korean B1+B6              | ETN 0    | EN taper post            |
| FB705       | 70            | 540     | D26        | 270    | 173    | 222    | Korean B1+B6              | ETN 1    | EN taper post            |
| FB708       | 70            | 740     | G78        | 260    | 180    | 186    | B7                        | ETN 1    | SAE S 3/8" side Terminal |
| FB712       | 71            | 670     | LB3        | 278    | 175    | 175    | B13                       | ETN 0    | EN taper post            |
| FB740       | 74            | 680     | L03        | 278    | 175    | 190    | B13                       | ETN 0    | EN taper post            |
| FB741       | 74            | 680     | L03        | 278    | 175    | 190    | B13                       | ETN 1    | EN taper post            |
| FB800       | 80            | 640     | L04        | 315    | 175    | 190    | B13                       | ETN 0    | EN taper post            |
| FB802       | 80            | 700     | LB4        | 315    | 175    | 175    | B13                       | ETN 0    | EN taper post            |
| FB852       | 85            | 760     | LB5        | 353    | 175    | 175    | B13                       | ETN 0    | EN taper post            |
| FB950       | 95            | 800     | L05        | 353    | 175    | 190    | B13                       | ETN 0    | EN taper post            |
| FB954       | 95            | 760     | D31        | 306    | 173    | 222    | Korean B1                 | ETN 0    | EN taper post            |
| FB955       | 95            | 760     | D31        | 306    | 173    | 222    | Korean B1                 | ETN 1    | EN taper post            |
| FB1000      | 100           | 720     | LH4        | 315    | 175    | 205    | B13                       | ETN 0    | EN taper post            |
| FB1100      | 110           | 850     | L06        | 392    | 175    | 190    | B13                       | ETN 0    | EN taper post            |

## FULMEN Standard

|       |    |     |     |     |     |     |     |       |               |
|-------|----|-----|-----|-----|-----|-----|-----|-------|---------------|
| FC440 | 44 | 360 | L01 | 207 | 175 | 190 | B13 | ETN 0 | EN taper post |
| FC542 | 54 | 500 | LB2 | 242 | 175 | 175 | B13 | ETN 0 | EN taper post |
| FC550 | 55 | 460 | L02 | 242 | 175 | 190 | B13 | ETN 0 | EN taper post |
| FC652 | 65 | 540 | LB3 | 278 | 175 | 175 | B13 | ETN 0 | EN taper post |
| FC700 | 70 | 640 | L03 | 278 | 175 | 190 | B13 | ETN 0 | EN taper post |
| FC900 | 90 | 720 | L05 | 353 | 175 | 190 | B13 | ETN 0 | EN taper post |

|             | Performance   |         | Dimensions |        |        |        | Technical characteristics |          |               |
|-------------|---------------|---------|------------|--------|--------|--------|---------------------------|----------|---------------|
| Part number | Capacity (Ah) | CCA (A) | Box size   | L (mm) | W (mm) | H (mm) | Hold Down                 | Polarity | Terminal Type |
| FC904       | 90            | 680     | D31        | 306    | 173    | 222    | Korean B1                 | ETN 0    | EN taper post |
| FC905       | 90            | 680     | D31        | 306    | 173    | 222    | Korean B1                 | ETN 1    | EN taper post |

# Batteries for Trucks, Buses, Construction, Agriculture

|             | Performance   |         | Dimensions      |        |        |           | Technical characteristics |               |  |
|-------------|---------------|---------|-----------------|--------|--------|-----------|---------------------------|---------------|--|
| Part number | Capacity (Ah) | CCA (A) | Box size L (mm) | W (mm) | H (mm) | Hold Down | Polarity                  | Terminal Type |  |

## FULMEN Endurance+PRO Gel

|         |     |      |     |     |     |     |    |       |               |
|---------|-----|------|-----|-----|-----|-----|----|-------|---------------|
| FD851T  | 85  | 350  | D02 | 349 | 175 | 235 | B0 | ETN 1 | EN taper post |
| FD2103  | 210 | 1030 | D06 | 518 | 274 | 240 | B0 | ETN 3 | EN taper post |
| FD2103T | 210 | 800  | D06 | 518 | 274 | 240 | B0 | ETN 3 | EN taper post |

## FULMEN StrongPRO EFB+

|        |     |      |     |     |     |     |    |       |               |
|--------|-----|------|-----|-----|-----|-----|----|-------|---------------|
| FE1403 | 140 | 800  | D04 | 513 | 189 | 223 | B0 | ETN 3 | EN taper post |
| FE1853 | 185 | 1100 | D05 | 513 | 223 | 223 | B0 | ETN 3 | EN taper post |
| FE2353 | 235 | 1200 | D06 | 518 | 274 | 240 | B0 | ETN 3 | EN taper post |

## FULMEN EndurancePRO EFB

|        |     |      |     |     |     |     |    |       |               |
|--------|-----|------|-----|-----|-----|-----|----|-------|---------------|
| FX1803 | 180 | 1000 | D05 | 513 | 223 | 223 | B0 | ETN 3 | EN taper post |
| FX2253 | 225 | 1150 | D06 | 518 | 274 | 240 | B0 | ETN 3 | EN taper post |

## FULMEN PowerPRO

|        |     |      |     |     |     |     |    |       |               |
|--------|-----|------|-----|-----|-----|-----|----|-------|---------------|
| FF1202 | 120 | 870  | D02 | 349 | 175 | 235 | B1 | ETN 0 | EN taper post |
| FF1250 | 125 | 850  | D03 | 349 | 175 | 285 | B0 | ETN 0 | EN taper post |
| FF1251 | 125 | 850  | D03 | 349 | 175 | 285 | B0 | ETN 1 | EN taper post |
| FF1453 | 145 | 900  | D04 | 513 | 189 | 223 | B0 | ETN 3 | EN taper post |
| FF1853 | 185 | 1150 | D05 | 513 | 223 | 223 | B0 | ETN 3 | EN taper post |
| FF2353 | 235 | 1300 | D06 | 518 | 274 | 240 | B0 | ETN 3 | EN taper post |

## FULMEN PowerPRO Agri&Construction

|        |     |      |     |     |     |     |     |       |                              |
|--------|-----|------|-----|-----|-----|-----|-----|-------|------------------------------|
| FJ050C | 50  | 800  | G34 | 260 | 173 | 206 | B7  | ETN 1 | SAE M 3/8"- 5/16" taper&stud |
| FJ1000 | 100 | 850  | L05 | 353 | 175 | 190 | B13 | ETN 0 | EN taper post                |
| FJ1355 | 135 | 1000 | DB8 | 514 | 175 | 210 | B3  | ETN 3 | EN taper post                |
| FJ1523 | 152 | 1130 | D04 | 513 | 189 | 223 | B0  | ETN 3 | EN taper post                |
| FJ1723 | 172 | 1390 | D05 | 513 | 223 | 223 | B0  | ETN 3 | EN taper post                |
| FJ2353 | 235 | 1450 | D06 | 518 | 274 | 240 | B0  | ETN 3 | EN taper post                |

|                        | Performance   |         | Dimensions      |        |        |           | Technical characteristics |               |                  |
|------------------------|---------------|---------|-----------------|--------|--------|-----------|---------------------------|---------------|------------------|
| Part number            | Capacity (Ah) | CCA (A) | Box size L (mm) | W (mm) | H (mm) | Hold Down | Polarity                  | Terminal Type |                  |
| <b>FULMEN StartPRO</b> |               |         |                 |        |        |           |                           |               |                  |
| FG1100                 | 110           | 750     | D02             | 349    | 175    | 235       | B0                        | ETN 0         | EN taper post    |
| FG1101                 | 110           | 750     | D02             | 349    | 175    | 235       | B0                        | ETN 1         | EN taper post    |
| FG1102                 | 110           | 750     | D02             | 349    | 175    | 235       | B1                        | ETN 0         | EN taper post    |
| FG110B                 | 110           | 950     | G31             | 330    | 173    | 240       | B0                        | ETN 9         | SAE A taper post |
| FG1203                 | 120           | 680     | D04             | 513    | 189    | 223       | B0                        | ETN 3         | EN taper post    |
| FG1206                 | 120           | 680     | D08             | 510    | 175    | 225       | B3                        | ETN 4         | EN taper post    |
| FG1250                 | 125           | 760     | D03             | 349    | 175    | 285       | B0                        | ETN 0         | EN taper post    |
| FG1353                 | 135           | 1000    | DB9             | 514    | 218    | 210       | B0                        | ETN 3         | EN taper post    |
| FG1355                 | 135           | 1000    | DB8             | 514    | 175    | 210       | B3                        | ETN 3         | EN taper post    |
| FG1402                 | 140           | 900     | ATM             | 508    | 175    | 205       | B1                        | ETN 0         | EN taper post    |
| FG1403                 | 140           | 800     | D04             | 513    | 189    | 223       | B0                        | ETN 3         | EN taper post    |
| FG1406                 | 140           | 800     | D08             | 510    | 175    | 225       | B3                        | ETN 4         | EN taper post    |
| FG145A                 | 145           | 1000    | F21             | 360    | 253    | 240       | B0                        | ETN 6         | EN taper post    |
| FG1553                 | 155           | 900     | D05             | 513    | 223    | 223       | B0                        | ETN 3         | EN taper post    |
| FG1803                 | 180           | 1000    | D05             | 513    | 223    | 223       | B0                        | ETN 3         | EN taper post    |
| FG1806                 | 180           | 1000    | D09             | 510    | 218    | 225       | B3                        | ETN 4         | EN taper post    |
| FG2253                 | 225           | 1200    | D06             | 518    | 274    | 240       | B0                        | ETN 3         | EN taper post    |
| FG2254                 | 225           | 1200    | D06             | 518    | 274    | 240       | B0                        | ETN 4         | EN taper post    |

# Batteries for Marine and Leisure

| Part number | Performance   |         |         |    | Dimensions |        |        |        | Technical characteristics |          |               |
|-------------|---------------|---------|---------|----|------------|--------|--------|--------|---------------------------|----------|---------------|
|             | Capacity (Ah) | CCA (A) | MCA (A) | WH | Box size   | L (mm) | W (mm) | H (mm) | Hold Down                 | Polarity | Terminal Type |

## EXIDE Equipment Li-Ion

|            |     |   |   |      |     |     |     |     |     |       |               |
|------------|-----|---|---|------|-----|-----|-----|-----|-----|-------|---------------|
| EV1300S/24 | 50  | - | - | 1300 | G77 | 307 | 170 | 216 | B0  | ETN 1 | Female M8     |
| EV640S     | 50  | - | - | 640  | D31 | 308 | 168 | 211 | B0  | ETN 1 | Female M8     |
| EV1250S    | 96  | - | - | 1250 | L05 | 355 | 176 | 190 | B13 | ETN 0 | EN taper post |
| EV1300S    | 100 | - | - | 1300 | D31 | 308 | 168 | 211 | B0  | ETN 1 | Female M8     |
| EV3800S/36 | 100 | - | - | 3800 | H52 | 520 | 269 | 221 | B0  | ETN 4 | Female M8     |
| EV2500S    | 200 | - | - | 2500 | F51 | 485 | 170 | 240 | B0  | ETN 1 | Female M8     |

## EXIDE Equipment GEL

|          |     |   |   |      |     |     |     |     |     |       |                          |
|----------|-----|---|---|------|-----|-----|-----|-----|-----|-------|--------------------------|
| ES290    | 25  | - | - | 290  | P24 | 166 | 175 | 125 | B0  | ETN 0 | Flat lug hole M5         |
| ES450    | 40  | - | - | 450  | LB1 | 207 | 175 | 175 | B4  | ETN 0 | EN full Ford lug         |
| ES650    | 56  | - | - | 650  | L03 | 278 | 175 | 190 | B13 | ETN 0 | EN taper post            |
| ES900    | 80  | - | - | 900  | L05 | 353 | 175 | 190 | B13 | ETN 0 | EN taper post            |
| ES950    | 85  | - | - | 950  | D02 | 330 | 171 | 235 | B0  | ETN 1 | EN taper post            |
| ES1200   | 110 | - | - | 1200 | D07 | 284 | 267 | 226 | B0  | ETN 2 | EN taper post            |
| ES1300   | 120 | - | - | 1300 | D03 | 345 | 171 | 283 | B0  | ETN 0 | EN taper post            |
| ES1350   | 120 | - | - | 1350 | D04 | 513 | 189 | 223 | B0  | ETN 3 | EN taper post            |
| ES1600   | 140 | - | - | 1600 | D05 | 513 | 223 | 223 | B0  | ETN 3 | EN taper post            |
| ES1000-6 | 195 | - | - | 1000 | GC2 | 244 | 190 | 275 | B0  | ETN 0 | EN taper post            |
| ES1100-6 | 200 | - | - | 1100 | GC2 | 244 | 190 | 275 | B0  | ETN 0 | M10 thread pos. and neg. |
| ES2400   | 210 | - | - | 2400 | D06 | 518 | 274 | 240 | B0  | ETN 3 | EN taper post            |

## EXIDE Equipment AGM

|        |     |   |   |      |     |     |     |     |     |       |               |
|--------|-----|---|---|------|-----|-----|-----|-----|-----|-------|---------------|
| EQ600  | 70  | - | - | 600  | L03 | 278 | 175 | 190 | B13 | ETN 0 | EN taper post |
| EQ800  | 95  | - | - | 800  | L05 | 353 | 175 | 190 | B13 | ETN 0 | EN taper post |
| EQ1000 | 120 | - | - | 1000 | D07 | 286 | 269 | 230 | B0  | ETN 2 | EN taper post |

## EXIDE Equipment

|        |     |   |   |      |     |     |     |     |     |       |               |
|--------|-----|---|---|------|-----|-----|-----|-----|-----|-------|---------------|
| ET550  | 80  | - | - | 550  | L03 | 278 | 175 | 190 | B13 | ETN 0 | EN taper post |
| ET650  | 100 | - | - | 650  | L05 | 353 | 175 | 190 | B13 | ETN 0 | EN taper post |
| ET950  | 135 | - | - | 950  | D04 | 513 | 189 | 223 | B0  | ETN 3 | EN taper post |
| ET1300 | 180 | - | - | 1300 | D05 | 513 | 223 | 223 | B0  | ETN 3 | EN taper post |

|             | Performance   |         |         |      | Dimensions |        |        |        | Technical characteristics |          |               |
|-------------|---------------|---------|---------|------|------------|--------|--------|--------|---------------------------|----------|---------------|
| Part number | Capacity (Ah) | CCA (A) | MCA (A) | WH   | Box size   | L (mm) | W (mm) | H (mm) | Hold Down                 | Polarity | Terminal Type |
| ET1600      | 230           | -       | -       | 1600 | D06        | 518    | 274    | 240    | B0                        | ETN 3    | EN taper post |

## EXIDE Dual AGM

|        |     |      |   |      |     |     |     |     |     |       |                              |
|--------|-----|------|---|------|-----|-----|-----|-----|-----|-------|------------------------------|
| EP450  | 50  | 750  | - | 450  | G34 | 260 | 173 | 206 | B7  | ETN 1 | SAE M 3/8"- 5/16" taper&stud |
| EP500  | 60  | 680  | - | -    | L02 | 242 | 175 | 190 | B13 | ETN 0 | EN taper post                |
| EP600  | 70  | 760  | - | 600  | L03 | 278 | 175 | 190 | B13 | ETN 0 | EN taper post                |
| EP800  | 95  | 850  | - | 800  | L05 | 353 | 175 | 190 | B13 | ETN 0 | EN taper post                |
| EP900  | 100 | 800  | - | 900  | G31 | 330 | 173 | 240 | B0  | ETN 1 | SAE M 3/8"- 5/16" taper&stud |
| EP1200 | 140 | 700  | - | 1200 | D04 | 513 | 189 | 223 | B0  | ETN 3 | EN taper post                |
| EP1500 | 180 | 900  | - | 1500 | D05 | 513 | 223 | 223 | B0  | ETN 3 | EN taper post                |
| EP2100 | 240 | 1200 | - | 2100 | D06 | 518 | 274 | 240 | B0  | ETN 3 | EN taper post                |

## EXIDE Dual EFB

|       |     |     |   |     |     |     |     |     |     |       |               |
|-------|-----|-----|---|-----|-----|-----|-----|-----|-----|-------|---------------|
| EZ600 | 70  | 760 | - | 600 | L03 | 278 | 175 | 190 | B13 | ETN 0 | EN taper post |
| EZ650 | 75  | 750 | - | 650 | D26 | 260 | 173 | 222 | B0  | ETN 1 | EN taper post |
| EZ850 | 100 | 900 | - | 850 | L05 | 353 | 175 | 190 | B13 | ETN 0 | EN taper post |

## EXIDE Dual

|       |     |      |   |     |     |     |     |     |              |       |               |
|-------|-----|------|---|-----|-----|-----|-----|-----|--------------|-------|---------------|
| ER350 | 80  | 510  | - | 350 | D26 | 270 | 173 | 222 | Korean B1+B6 | ETN 1 | EN taper post |
| ER450 | 95  | 650  | - | 450 | D31 | 306 | 173 | 222 | Korean B1    | ETN 1 | EN taper post |
| ER550 | 115 | 760  | - | 550 | D02 | 349 | 175 | 235 | B0           | ETN 1 | EN taper post |
| ER600 | 120 | 800  | - | -   | D03 | 349 | 175 | 285 | B0           | ETN 1 | EN taper post |
| ER850 | 180 | 1000 | - | 850 | D05 | 513 | 223 | 223 | B0           | ETN 3 | EN taper post |

## EXIDE Start AGM

|        |     |     |      |   |     |     |     |     |    |       |                              |
|--------|-----|-----|------|---|-----|-----|-----|-----|----|-------|------------------------------|
| EM1000 | 50  | 800 | 1000 | - | G34 | 260 | 173 | 206 | B7 | ETN 1 | SAE M 3/8"- 5/16" taper&stud |
| EM960  | 100 | 800 | 960  | - | G31 | 330 | 173 | 240 | B0 | ETN 1 | SAE M 3/8" taper&stud        |

## EXIDE Start

|       |    |     |     |   |     |     |     |     |     |       |               |
|-------|----|-----|-----|---|-----|-----|-----|-----|-----|-------|---------------|
| EN500 | 50 | 450 | 500 | - | L01 | 207 | 175 | 190 | B13 | ETN 0 | EN taper post |
| EN600 | 62 | 540 | 600 | - | L02 | 242 | 175 | 190 | B13 | ETN 0 | EN taper post |
| EN750 | 74 | 680 | 750 | - | L03 | 278 | 175 | 190 | B13 | ETN 0 | EN taper post |



|             | Performance   |         |         |    | Dimensions |        |        |        | Technical characteristics |          |               |
|-------------|---------------|---------|---------|----|------------|--------|--------|--------|---------------------------|----------|---------------|
| Part number | Capacity (Ah) | CCA (A) | MCA (A) | WH | Box size   | L (mm) | W (mm) | H (mm) | Hold Down                 | Polarity | Terminal Type |
| EN800       | 90            | 720     | 800     | -  | L05        | 353    | 175    | 190    | B13                       | ETN 0    | EN taper post |
| EN850       | 110           | 750     | 850     | -  | D02        | 349    | 175    | 235    | B0                        | ETN 1    | EN taper post |
| EN900       | 140           | 800     | 900     | -  | D04        | 513    | 189    | 223    | B0                        | ETN 3    | EN taper post |
| EN1100      | 180           | 1000    | 1100    | -  | D05        | 513    | 223    | 223    | B0                        | ETN 3    | EN taper post |

## EXIDE Maxxima

|       |    |     |   |   |     |     |     |     |    |       |                          |
|-------|----|-----|---|---|-----|-----|-----|-----|----|-------|--------------------------|
| EX900 | 50 | 800 | - | - | G34 | 260 | 173 | 206 | B7 | ETN 9 | SAE S 3/8" side Terminal |
|-------|----|-----|---|---|-----|-----|-----|-----|----|-------|--------------------------|

## EXIDE Vintage

|         |     |      |   |   |     |     |     |     |     |       |                     |
|---------|-----|------|---|---|-----|-----|-----|-----|-----|-------|---------------------|
| EU72L   | 72  | 640  | - | - | L03 | 278 | 175 | 190 | B13 | ETN 1 | EN taper post       |
| EU77-6  | 77  | 650  | - | - | H02 | 215 | 169 | 184 | B6  | ETN 0 | EN taper post       |
| EU80-6  | 80  | 600  | - | - | M02 | 158 | 165 | 220 | B0  | ETN 0 | EN taper post       |
| EU140-6 | 140 | 900  | - | - | M04 | 257 | 175 | 236 | B1  | ETN 0 | EN taper post       |
| EU165-6 | 165 | 900  | - | - | M05 | 330 | 174 | 234 | B0  | ETN 0 | EN taper post       |
| EU200-6 | 200 | 1150 | - | - | M06 | 398 | 174 | 234 | B0  | ETN 0 | Twin EN taper posts |
| EU260-6 | 260 | 1300 | - | - | M08 | 345 | 172 | 286 | B0  | ETN 0 | EN taper post       |

# Batteries for Motorcycles, ATVs, Snowmobiles, Garden

|             | Performance   |         |    | Dimensions |        |        |        | Technical characteristics |          |               |
|-------------|---------------|---------|----|------------|--------|--------|--------|---------------------------|----------|---------------|
| Part number | Capacity (Ah) | CCA (A) | WH | Box size   | L (mm) | W (mm) | H (mm) | Hold Down                 | Polarity | Terminal Type |

## EXIDE Li-Ion

|         |     |     |    |     |     |    |     |    |       |                       |
|---------|-----|-----|----|-----|-----|----|-----|----|-------|-----------------------|
| ELTZ5S  | 2   | 120 | 24 | C35 | 115 | 70 | 85  | B0 | ETN 0 | M12                   |
| ELTZ7S  | 2.4 | 150 | 29 | C35 | 115 | 70 | 85  | B0 | ETN 0 | M12                   |
| ELT9B   | 3   | 190 | 36 | C50 | 150 | 65 | 95  | B0 | ETN 1 | M12                   |
| ELTX9   | 3   | 180 | 36 | C54 | 150 | 90 | 105 | B0 | ETN 1 | M12                   |
| ELTX12  | 3.5 | 210 | 42 | C53 | 150 | 90 | 95  | B0 | ETN 1 | M12                   |
| ELTX14H | 4   | 240 | 48 | C53 | 150 | 90 | 95  | B0 | ETN 1 | M12                   |
| ELTZ10S | 4   | 230 | 48 | C53 | 150 | 90 | 95  | B0 | ETN 1 | M12                   |
| ELT12B  | 5   | 260 | 60 | C51 | 150 | 70 | 130 | B0 | ETN 1 | M12                   |
| ELTZ14S | 5   | 290 | 60 | C53 | 150 | 90 | 95  | B0 | ETN 1 | M12                   |
| ELTX20H | 7   | 380 | 84 | C77 | 175 | 90 | 130 | B0 | ETN 1 | M12 (Squad Terminals) |

## EXIDE GEL

|          |    |     |   |     |     |     |     |    |       |                  |
|----------|----|-----|---|-----|-----|-----|-----|----|-------|------------------|
| GEL12-19 | 19 | 170 | - | C66 | 185 | 80  | 170 | B0 | ETN 0 | M11              |
| GEL12-30 | 30 | 180 | - | U01 | 197 | 132 | 186 | B0 | ETN 1 | EN full Ford lug |

## EXIDE AGM Ready

|            |     |     |   |     |     |    |     |    |       |                |
|------------|-----|-----|---|-----|-----|----|-----|----|-------|----------------|
| AGM12-4    | 3   | 50  | - | C35 | 115 | 70 | 85  | B0 | ETN 0 | M04            |
| AGM12-5    | 4   | 70  | - | C36 | 115 | 70 | 105 | B0 | ETN 0 | M04            |
| AGM12-6    | 6   | 90  | - | C53 | 150 | 90 | 95  | B0 | ETN 1 | M04            |
| AGM12-7    | 6   | 100 | - | C36 | 115 | 70 | 105 | B0 | ETN 0 | M04            |
| AGM12-6.5  | 6.5 | 85  | - | C50 | 150 | 65 | 95  | B0 | ETN 1 | M04            |
| AGM12-7F   | 7   | 85  | - | C50 | 150 | 65 | 95  | B0 | ETN 3 | Faston S (4,8) |
| AGM12-7.1  | 8   | 110 | - | C73 | 150 | 70 | 105 | B0 | ETN 1 | M04            |
| AGM12-7.5  | 8   | 120 | - | C54 | 150 | 90 | 105 | B0 | ETN 1 | M12            |
| AGM12-8    | 9   | 145 | - | C53 | 150 | 90 | 95  | B0 | ETN 1 | M12            |
| AGM12-9    | 9   | 120 | - | C43 | 135 | 75 | 140 | B0 | ETN 1 | M04            |
| AGM12-10   | 10  | 150 | - | C55 | 150 | 90 | 130 | B0 | ETN 1 | M04            |
| AGM12-10.5 | 10  | 160 | - | C51 | 150 | 70 | 130 | B0 | ETN 1 | M04            |
| AGM12-11   | 11  | 205 | - | C74 | 150 | 90 | 110 | B0 | ETN 1 | M04            |
| AGM12-12   | 12  | 200 | - | C56 | 150 | 90 | 145 | B0 | ETN 1 | M04            |

|             | Performance   |         |    | Dimensions |        |        |        | Technical characteristics |          |                |
|-------------|---------------|---------|----|------------|--------|--------|--------|---------------------------|----------|----------------|
| Part number | Capacity (Ah) | CCA (A) | WH | Box size   | L (mm) | W (mm) | H (mm) | Hold Down                 | Polarity | Terminal Type  |
| AGM12-12.1  | 12            | 200     | -  | C56        | 150    | 90     | 145    | B0                        | ETN 0    | M04            |
| AGM12-12F   | 12            | 150     | -  | C76        | 150    | 100    | 100    | B0                        | ETN 3    | Faston S (4,8) |
| AGM12-12M   | 12            | 200     | -  | C56        | 150    | 90     | 145    | B0                        | ETN 1    | M12            |
| AGM12-14    | 12            | 210     | -  | C49        | 135    | 90     | 165    | B0                        | ETN 0    | M04            |
| AGM12-14.1  | 12            | 210     | -  | C49        | 135    | 90     | 165    | B0                        | ETN 1    | M04            |
| AGM12-15    | 14            | 215     | -  | C57        | 150    | 90     | 160    | B0                        | ETN 1    | M04            |
| AGM12-16    | 16            | 200     | -  | C57        | 150    | 90     | 160    | B0                        | ETN 1    | M04            |
| AGM12-17    | 18            | 230     | -  | C57        | 150    | 90     | 160    | B0                        | ETN 1    | M04            |
| AGM12-18    | 18            | 250     | -  | C64        | 180    | 75     | 165    | B0                        | ETN 0    | M11            |
| AGM12-19    | 18            | 270     | -  | C61        | 175    | 90     | 155    | B0                        | ETN 0    | M04            |
| AGM12-19.1  | 18            | 270     | -  | C61        | 175    | 90     | 155    | B0                        | ETN 1    | M04            |
| AGM12-23    | 21            | 350     | -  | C71        | 205    | 90     | 165    | B0                        | ETN 0    | M04            |
| AGM12-31    | 30            | 430     | -  | C52        | 165    | 130    | 175    | B0                        | ETN 0    | M04            |

## EXIDE AGM MC (Dry)

|             |     |     |   |     |     |    |     |    |       |     |
|-------------|-----|-----|---|-----|-----|----|-----|----|-------|-----|
| ET4B-BS     | 2.3 | 35  | - | C33 | 115 | 40 | 85  | B0 | ETN 4 | M13 |
| ETR4A-BS    | 2.3 | 35  | - | C34 | 115 | 50 | 85  | B0 | ETN 4 | M14 |
| ETX4L-BS    | 3   | 50  | - | C35 | 115 | 70 | 85  | B0 | ETN 0 | M04 |
| ETX5L-BS    | 4   | 70  | - | C36 | 115 | 70 | 105 | B0 | ETN 0 | M04 |
| ETZ7-BS     | 6   | 100 | - | C36 | 115 | 70 | 105 | B0 | ETN 0 | M04 |
| ETX7A-BS    | 6   | 90  | - | C53 | 150 | 90 | 95  | B0 | ETN 1 | M04 |
| ETX7L-BS    | 6   | 100 | - | C37 | 115 | 70 | 130 | B0 | ETN 0 | M04 |
| ET7B-BS     | 6.5 | 85  | - | C50 | 150 | 65 | 95  | B0 | ETN 1 | M04 |
| ET9B-BS     | 8   | 110 | - | C73 | 150 | 70 | 105 | B0 | ETN 1 | M04 |
| ETX9-BS     | 8   | 120 | - | C54 | 150 | 90 | 105 | B0 | ETN 1 | M12 |
| ETZ10-BS    | 8.6 | 145 | - | C53 | 150 | 90 | 95  | B0 | ETN 1 | M12 |
| ETX9C-BS    | 9   | 120 | - | C43 | 135 | 75 | 140 | B0 | ETN 1 | M04 |
| ET12A-BS    | 9.5 | 130 | - | C54 | 150 | 90 | 105 | B0 | ETN 1 | M04 |
| ET12B-BS    | 10  | 160 | - | C51 | 150 | 70 | 130 | B0 | ETN 1 | M04 |
| ETX12-BS    | 10  | 150 | - | C55 | 150 | 90 | 130 | B0 | ETN 1 | M04 |
| ETZ14-BS    | 11  | 205 | - | C74 | 150 | 90 | 110 | B0 | ETN 1 | M04 |
| ETX14AH-BS  | 12  | 210 | - | C49 | 135 | 90 | 165 | B0 | ETN 1 | M04 |
| ETX14AHL-BS | 12  | 210 | - | C49 | 135 | 90 | 165 | B0 | ETN 0 | M04 |
| ETX14-BS    | 12  | 200 | - | C56 | 150 | 90 | 145 | B0 | ETN 1 | M04 |
| ETX14L-BS   | 12  | 200 | - | C56 | 150 | 90 | 145 | B0 | ETN 0 | M04 |
| ET14B-BS    | 12  | 190 | - | C75 | 150 | 70 | 145 | B0 | ETN 1 | M04 |
| ETX16-BS    | 14  | 215 | - | C57 | 150 | 90 | 160 | B0 | ETN 1 | M04 |

|             | Performance   |         |    | Dimensions |        |        |        | Technical characteristics |          |               |
|-------------|---------------|---------|----|------------|--------|--------|--------|---------------------------|----------|---------------|
| Part number | Capacity (Ah) | CCA (A) | WH | Box size   | L (mm) | W (mm) | H (mm) | Hold Down                 | Polarity | Terminal Type |
| ETX20CH-BS  | 18            | 230     | -  | C57        | 150    | 90     | 160    | B0                        | ETN 1    | M04           |
| ETX20H-BS   | 18            | 270     | -  | C61        | 175    | 90     | 155    | B0                        | ETN 1    | M04           |
| ETX20HL-BS  | 18            | 270     | -  | C61        | 175    | 90     | 155    | B0                        | ETN 0    | M04           |
| ETX24HL-BS  | 21            | 350     | -  | C71        | 205    | 90     | 165    | B0                        | ETN 0    | M04           |

## EXIDE Conventional

|             |     |     |   |     |     |     |     |    |       |     |
|-------------|-----|-----|---|-----|-----|-----|-----|----|-------|-----|
| EB4L-B      | 4   | 50  | - | C39 | 120 | 70  | 95  | B0 | ETN 0 | M04 |
| EB5L-B      | 5   | 65  | - | C38 | 120 | 60  | 130 | B0 | ETN 0 | M06 |
| 12N5-3B     | 5   | 40  | - | C38 | 120 | 60  | 130 | B0 | ETN 0 | M06 |
| 12N5,5-3B   | 5.5 | 45  | - | C41 | 135 | 60  | 130 | B0 | ETN 0 | M06 |
| 6N6-3B-1    | 6   | 40  | - | C09 | 100 | 55  | 110 | B0 | ETN 2 | M06 |
| 12N7-3B     | 7   | 75  | - | C42 | 135 | 75  | 135 | B0 | ETN 0 | M06 |
| EB7-A       | 8   | 85  | - | C42 | 135 | 75  | 135 | B0 | ETN 1 | M06 |
| EB7L-B      | 8   | 85  | - | C42 | 135 | 75  | 135 | B0 | ETN 0 | M06 |
| EB9-B       | 9   | 100 | - | C43 | 135 | 75  | 140 | B0 | ETN 1 | M06 |
| 12N9-3B     | 9   | 85  | - | C43 | 135 | 75  | 140 | B0 | ETN 0 | M06 |
| 12N9-4B-1   | 9   | 85  | - | C43 | 135 | 75  | 140 | B0 | ETN 1 | M06 |
| EB10L-B     | 11  | 130 | - | C47 | 135 | 90  | 145 | B0 | ETN 0 | M06 |
| EB10L-B2    | 11  | 130 | - | C47 | 135 | 90  | 145 | B0 | ETN 0 | M08 |
| 6N11A-1B    | 11  | 95  | - | C10 | 120 | 60  | 130 | B0 | ETN 0 | M06 |
| EB10L-A2    | 11  | 130 | - | C47 | 135 | 90  | 145 | B0 | ETN 0 | M08 |
| 12N12A-4A-1 | 12  | 115 | - | C45 | 135 | 80  | 160 | B0 | ETN 1 | M06 |
| EB12A-A     | 12  | 165 | - | C45 | 135 | 80  | 160 | B0 | ETN 1 | M06 |
| EB12AL-A    | 12  | 165 | - | C45 | 135 | 80  | 160 | B0 | ETN 0 | M06 |
| EB12AL-A2   | 12  | 165 | - | C45 | 135 | 80  | 160 | B0 | ETN 0 | M04 |
| 12N14-3A    | 14  | 130 | - | C49 | 135 | 90  | 165 | B0 | ETN 0 | M08 |
| EB14-A2     | 14  | 145 | - | C49 | 135 | 90  | 165 | B0 | ETN 1 | M08 |
| EB14-B2     | 14  | 145 | - | C49 | 135 | 90  | 165 | B0 | ETN 1 | M08 |
| EB14L-A2    | 14  | 145 | - | C49 | 135 | 90  | 165 | B0 | ETN 0 | M08 |
| EB14L-B2    | 14  | 145 | - | C49 | 135 | 90  | 165 | B0 | ETN 0 | M08 |
| EB16AL-A2   | 16  | 175 | - | C70 | 205 | 70  | 165 | B0 | ETN 0 | M02 |
| EB18L-A     | 18  | 190 | - | C65 | 180 | 90  | 160 | B0 | ETN 0 | M07 |
| EB16-B      | 19  | 190 | - | C62 | 175 | 100 | 155 | B0 | ETN 1 | M06 |
| EB16CL-B    | 19  | 190 | - | C63 | 175 | 100 | 175 | B0 | ETN 0 | M04 |
| EB16L-B     | 19  | 190 | - | C62 | 175 | 100 | 155 | B0 | ETN 0 | M06 |
| E50-N18L-A  | 20  | 260 | - | C71 | 205 | 90  | 165 | B0 | ETN 0 | M07 |
| E50-N18L-A3 | 20  | 260 | - | C71 | 205 | 90  | 165 | B0 | ETN 0 | M04 |

|             | Performance   |         |    | Dimensions |        |        |        | Technical characteristics |          |               |
|-------------|---------------|---------|----|------------|--------|--------|--------|---------------------------|----------|---------------|
| Part number | Capacity (Ah) | CCA (A) | WH | Box size   | L (mm) | W (mm) | H (mm) | Hold Down                 | Polarity | Terminal Type |
| 12Y16A-3A   | 20            | 210     | -  | C66        | 185    | 80     | 170    | B0                        | ETN 0    | M11           |
| 12N24-3A    | 24            | 220     | -  | C67        | 185    | 125    | 175    | B0                        | ETN 0    | M03           |
| 12N24-4A    | 24            | 220     | -  | C67        | 185    | 125    | 175    | B0                        | ETN 1    | M03           |
| U1-9        | 24            | 240     | -  | C69        | 195    | 130    | 180    | B0                        | ETN 1    | M11           |
| E60-N24L-A  | 28            | 280     | -  | C67        | 185    | 125    | 175    | B0                        | ETN 0    | M11           |
| U1R-11      | 30            | 300     | -  | C69        | 195    | 130    | 180    | B0                        | ETN 0    | M11           |
| E60-N30-A   | 30            | 300     | -  | C68        | 185    | 130    | 170    | B0                        | ETN 1    | M11           |
| E60-N30L-A  | 30            | 300     | -  | C68        | 185    | 130    | 170    | B0                        | ETN 0    | M11           |
| E60-N30L-B  | 30            | 300     | -  | C68        | 185    | 130    | 170    | B0                        | ETN 0    | M11           |
| EB30L-B     | 30            | 300     | -  | C52        | 165    | 130    | 175    | B0                        | ETN 0    | M04           |

## EXIDE Garden

|         |    |     |   |     |     |     |     |    |       |                   |
|---------|----|-----|---|-----|-----|-----|-----|----|-------|-------------------|
| U1L-250 | 24 | 250 | - | U01 | 197 | 132 | 186 | B0 | ETN 1 | EN small Ford lug |
| U1R-250 | 24 | 250 | - | U01 | 197 | 132 | 186 | B0 | ETN 0 | EN small Ford lug |

Design, features and specifications are subject to change without notice. We disclaim any representation or warranty, express or implied, concerning the data or recommendations, and in no event shall be liable for any loss or damage claimed to have arisen as a result. Some products may not be available in your local market.