



Batteries for Trucks, Buses, Construction, Agriculture

| | Performance | | Dimensions | | | Technical characteristics | | |
|-------------|---------------|---------|-----------------|--------|--------|---------------------------|----------|---------------|
| Part number | Capacity (Ah) | CCA (A) | Box size L (mm) | W (mm) | H (mm) | Hold Down | Polarity | Terminal Type |

CENTRA Endurance+PRO Gel

| | | | | | | | | | |
|--------|----|-----|-----|-----|-----|-----|----|-------|---------------|
| CD851T | 85 | 350 | D02 | 349 | 175 | 235 | B0 | ETN 1 | EN taper post |
|--------|----|-----|-----|-----|-----|-----|----|-------|---------------|

Batteries for Marine and Leisure

| Part number | Performance | | | | Dimensions | | | | Technical characteristics | | |
|-------------|---------------|---------|---------|----|------------|--------|--------|--------|---------------------------|----------|---------------|
| | Capacity (Ah) | CCA (A) | MCA (A) | WH | Box size | L (mm) | W (mm) | H (mm) | Hold Down | Polarity | Terminal Type |

EXIDE Equipment Li-Ion

| | | | | | | | | | | | |
|------------|-----|---|---|------|-----|-----|-----|-----|-----|-------|---------------|
| EV1300S/24 | 50 | - | - | 1300 | G77 | 307 | 170 | 216 | B0 | ETN 1 | Female M8 |
| EV640S | 50 | - | - | 640 | D31 | 308 | 168 | 211 | B0 | ETN 1 | Female M8 |
| EV1250S | 96 | - | - | 1250 | L05 | 355 | 176 | 190 | B13 | ETN 0 | EN taper post |
| EV1300S | 100 | - | - | 1300 | D31 | 308 | 168 | 211 | B0 | ETN 1 | Female M8 |
| EV3800S/36 | 100 | - | - | 3800 | H52 | 520 | 269 | 221 | B0 | ETN 4 | Female M8 |
| EV2500S | 200 | - | - | 2500 | F51 | 485 | 170 | 240 | B0 | ETN 1 | Female M8 |

EXIDE Equipment GEL

| | | | | | | | | | | | |
|----------|-----|---|---|------|-----|-----|-----|-----|-----|-------|--------------------------|
| ES290 | 25 | - | - | 290 | P24 | 166 | 175 | 125 | B0 | ETN 0 | Flat lug hole M5 |
| ES450 | 40 | - | - | 450 | LB1 | 207 | 175 | 175 | B4 | ETN 0 | EN full Ford lug |
| ES650 | 56 | - | - | 650 | L03 | 278 | 175 | 190 | B13 | ETN 0 | EN taper post |
| ES900 | 80 | - | - | 900 | L05 | 353 | 175 | 190 | B13 | ETN 0 | EN taper post |
| ES950 | 85 | - | - | 950 | D02 | 330 | 171 | 235 | B0 | ETN 1 | EN taper post |
| ES1200 | 110 | - | - | 1200 | D07 | 284 | 267 | 226 | B0 | ETN 2 | EN taper post |
| ES1300 | 120 | - | - | 1300 | D03 | 345 | 171 | 283 | B0 | ETN 0 | EN taper post |
| ES1350 | 120 | - | - | 1350 | D04 | 513 | 189 | 223 | B0 | ETN 3 | EN taper post |
| ES1600 | 140 | - | - | 1600 | D05 | 513 | 223 | 223 | B0 | ETN 3 | EN taper post |
| ES1000-6 | 195 | - | - | 1000 | GC2 | 244 | 190 | 275 | B0 | ETN 0 | EN taper post |
| ES1100-6 | 200 | - | - | 1100 | GC2 | 244 | 190 | 275 | B0 | ETN 0 | M10 thread pos. and neg. |
| ES2400 | 210 | - | - | 2400 | D06 | 518 | 274 | 240 | B0 | ETN 3 | EN taper post |

EXIDE Equipment AGM

| | | | | | | | | | | | |
|--------|-----|---|---|------|-----|-----|-----|-----|-----|-------|---------------|
| EQ600 | 70 | - | - | 600 | L03 | 278 | 175 | 190 | B13 | ETN 0 | EN taper post |
| EQ800 | 95 | - | - | 800 | L05 | 353 | 175 | 190 | B13 | ETN 0 | EN taper post |
| EQ1000 | 120 | - | - | 1000 | D07 | 286 | 269 | 230 | B0 | ETN 2 | EN taper post |

EXIDE Equipment

| | | | | | | | | | | | |
|--------|-----|---|---|------|-----|-----|-----|-----|-----|-------|---------------|
| ET550 | 80 | - | - | 550 | L03 | 278 | 175 | 190 | B13 | ETN 0 | EN taper post |
| ET650 | 100 | - | - | 650 | L05 | 353 | 175 | 190 | B13 | ETN 0 | EN taper post |
| ET950 | 135 | - | - | 950 | D04 | 513 | 189 | 223 | B0 | ETN 3 | EN taper post |
| ET1300 | 180 | - | - | 1300 | D05 | 513 | 223 | 223 | B0 | ETN 3 | EN taper post |

| | Performance | | | | Dimensions | | | | Technical characteristics | | |
|-------------|---------------|---------|---------|------|------------|--------|--------|--------|---------------------------|----------|---------------|
| Part number | Capacity (Ah) | CCA (A) | MCA (A) | WH | Box size | L (mm) | W (mm) | H (mm) | Hold Down | Polarity | Terminal Type |
| ET1600 | 230 | - | - | 1600 | D06 | 518 | 274 | 240 | B0 | ETN 3 | EN taper post |

EXIDE Dual AGM

| | | | | | | | | | | | |
|--------|-----|------|---|------|-----|-----|-----|-----|-----|-------|------------------------------|
| EP450 | 50 | 750 | - | 450 | G34 | 260 | 173 | 206 | B7 | ETN 1 | SAE M 3/8"- 5/16" taper&stud |
| EP500 | 60 | 680 | - | - | L02 | 242 | 175 | 190 | B13 | ETN 0 | EN taper post |
| EP600 | 70 | 760 | - | 600 | L03 | 278 | 175 | 190 | B13 | ETN 0 | EN taper post |
| EP800 | 95 | 850 | - | 800 | L05 | 353 | 175 | 190 | B13 | ETN 0 | EN taper post |
| EP900 | 100 | 800 | - | 900 | G31 | 330 | 173 | 240 | B0 | ETN 1 | SAE M 3/8"- 5/16" taper&stud |
| EP1200 | 140 | 700 | - | 1200 | D04 | 513 | 189 | 223 | B0 | ETN 3 | EN taper post |
| EP1500 | 180 | 900 | - | 1500 | D05 | 513 | 223 | 223 | B0 | ETN 3 | EN taper post |
| EP2100 | 240 | 1200 | - | 2100 | D06 | 518 | 274 | 240 | B0 | ETN 3 | EN taper post |

EXIDE Dual EFB

| | | | | | | | | | | | |
|-------|-----|-----|---|-----|-----|-----|-----|-----|-----|-------|---------------|
| EZ600 | 70 | 760 | - | 600 | L03 | 278 | 175 | 190 | B13 | ETN 0 | EN taper post |
| EZ650 | 75 | 750 | - | 650 | D26 | 260 | 173 | 222 | B0 | ETN 1 | EN taper post |
| EZ850 | 100 | 900 | - | 850 | L05 | 353 | 175 | 190 | B13 | ETN 0 | EN taper post |

EXIDE Dual

| | | | | | | | | | | | |
|-------|-----|------|---|-----|-----|-----|-----|-----|--------------|-------|---------------|
| ER350 | 80 | 510 | - | 350 | D26 | 270 | 173 | 222 | Korean B1+B6 | ETN 1 | EN taper post |
| ER450 | 95 | 650 | - | 450 | D31 | 306 | 173 | 222 | Korean B1 | ETN 1 | EN taper post |
| ER550 | 115 | 760 | - | 550 | D02 | 349 | 175 | 235 | B0 | ETN 1 | EN taper post |
| ER600 | 120 | 800 | - | - | D03 | 349 | 175 | 285 | B0 | ETN 1 | EN taper post |
| ER850 | 180 | 1000 | - | 850 | D05 | 513 | 223 | 223 | B0 | ETN 3 | EN taper post |

EXIDE Start AGM

| | | | | | | | | | | | |
|--------|-----|-----|------|---|-----|-----|-----|-----|----|-------|------------------------------|
| EM1000 | 50 | 800 | 1000 | - | G34 | 260 | 173 | 206 | B7 | ETN 1 | SAE M 3/8"- 5/16" taper&stud |
| EM960 | 100 | 800 | 960 | - | G31 | 330 | 173 | 240 | B0 | ETN 1 | SAE M 3/8" taper&stud |

EXIDE Start

| | | | | | | | | | | | |
|-------|----|-----|-----|---|-----|-----|-----|-----|-----|-------|---------------|
| EN500 | 50 | 450 | 500 | - | L01 | 207 | 175 | 190 | B13 | ETN 0 | EN taper post |
| EN600 | 62 | 540 | 600 | - | L02 | 242 | 175 | 190 | B13 | ETN 0 | EN taper post |
| EN750 | 74 | 680 | 750 | - | L03 | 278 | 175 | 190 | B13 | ETN 0 | EN taper post |

| | Performance | | | | Dimensions | | | | Technical characteristics | | |
|-------------|---------------|---------|---------|----|------------|--------|--------|--------|---------------------------|----------|---------------|
| Part number | Capacity (Ah) | CCA (A) | MCA (A) | WH | Box size | L (mm) | W (mm) | H (mm) | Hold Down | Polarity | Terminal Type |
| EN800 | 90 | 720 | 800 | - | L05 | 353 | 175 | 190 | B13 | ETN 0 | EN taper post |
| EN850 | 110 | 750 | 850 | - | D02 | 349 | 175 | 235 | B0 | ETN 1 | EN taper post |
| EN900 | 140 | 800 | 900 | - | D04 | 513 | 189 | 223 | B0 | ETN 3 | EN taper post |
| EN1100 | 180 | 1000 | 1100 | - | D05 | 513 | 223 | 223 | B0 | ETN 3 | EN taper post |

EXIDE Maxxima

| | | | | | | | | | | | |
|-------|----|-----|---|---|-----|-----|-----|-----|----|-------|--------------------------|
| EX900 | 50 | 800 | - | - | G34 | 260 | 173 | 206 | B7 | ETN 9 | SAE S 3/8" side Terminal |
|-------|----|-----|---|---|-----|-----|-----|-----|----|-------|--------------------------|

EXIDE Vintage

| | | | | | | | | | | | |
|---------|-----|------|---|---|-----|-----|-----|-----|----|-------|---------------------|
| EU77-6 | 77 | 650 | - | - | H02 | 215 | 169 | 184 | B6 | ETN 0 | EN taper post |
| EU80-6 | 80 | 600 | - | - | M02 | 158 | 165 | 220 | B0 | ETN 0 | EN taper post |
| EU140-6 | 140 | 900 | - | - | M04 | 257 | 175 | 236 | B1 | ETN 0 | EN taper post |
| EU165-6 | 165 | 900 | - | - | M05 | 330 | 174 | 234 | B0 | ETN 0 | EN taper post |
| EU200-6 | 200 | 1150 | - | - | M06 | 398 | 174 | 234 | B0 | ETN 0 | Twin EN taper posts |
| EU260-6 | 260 | 1300 | - | - | M08 | 345 | 172 | 286 | B0 | ETN 0 | EN taper post |

Batteries for Motorcycles, ATVs, Snowmobiles, Garden

| | Performance | | | Dimensions | | | | Technical characteristics | | |
|-------------|---------------|---------|----|------------|--------|--------|--------|---------------------------|----------|---------------|
| Part number | Capacity (Ah) | CCA (A) | WH | Box size | L (mm) | W (mm) | H (mm) | Hold Down | Polarity | Terminal Type |

EXIDE Li-Ion

| | | | | | | | | | | |
|---------|-----|-----|----|-----|-----|----|-----|----|-------|-----------------------|
| ELTZ5S | 2 | 120 | 24 | C35 | 115 | 70 | 85 | B0 | ETN 0 | M12 |
| ELTZ7S | 2.4 | 150 | 29 | C35 | 115 | 70 | 85 | B0 | ETN 0 | M12 |
| ELT9B | 3 | 190 | 36 | C50 | 150 | 65 | 95 | B0 | ETN 1 | M12 |
| ELTX9 | 3 | 180 | 36 | C54 | 150 | 90 | 105 | B0 | ETN 1 | M12 |
| ELTX12 | 3.5 | 210 | 42 | C53 | 150 | 90 | 95 | B0 | ETN 1 | M12 |
| ELTX14H | 4 | 240 | 48 | C53 | 150 | 90 | 95 | B0 | ETN 1 | M12 |
| ELTZ10S | 4 | 230 | 48 | C53 | 150 | 90 | 95 | B0 | ETN 1 | M12 |
| ELT12B | 5 | 260 | 60 | C51 | 150 | 70 | 130 | B0 | ETN 1 | M12 |
| ELTZ14S | 5 | 290 | 60 | C53 | 150 | 90 | 95 | B0 | ETN 1 | M12 |
| ELTX20H | 7 | 380 | 84 | C77 | 175 | 90 | 130 | B0 | ETN 1 | M12 (Squad Terminals) |

EXIDE GEL

| | | | | | | | | | | |
|----------|----|-----|---|-----|-----|-----|-----|----|-------|------------------|
| GEL12-19 | 19 | 170 | - | C66 | 185 | 80 | 170 | B0 | ETN 0 | M11 |
| GEL12-30 | 30 | 180 | - | U01 | 197 | 132 | 186 | B0 | ETN 1 | EN full Ford lug |

EXIDE AGM Ready

| | | | | | | | | | | |
|------------|-----|-----|---|-----|-----|----|-----|----|-------|----------------|
| AGM12-4 | 3 | 50 | - | C35 | 115 | 70 | 85 | B0 | ETN 0 | M04 |
| AGM12-5 | 4 | 70 | - | C36 | 115 | 70 | 105 | B0 | ETN 0 | M04 |
| AGM12-6 | 6 | 90 | - | C53 | 150 | 90 | 95 | B0 | ETN 1 | M04 |
| AGM12-7 | 6 | 100 | - | C36 | 115 | 70 | 105 | B0 | ETN 0 | M04 |
| AGM12-6.5 | 6.5 | 85 | - | C50 | 150 | 65 | 95 | B0 | ETN 1 | M04 |
| AGM12-7F | 7 | 85 | - | C50 | 150 | 65 | 95 | B0 | ETN 3 | Faston S (4,8) |
| AGM12-7.1 | 8 | 110 | - | C73 | 150 | 70 | 105 | B0 | ETN 1 | M04 |
| AGM12-7.5 | 8 | 120 | - | C54 | 150 | 90 | 105 | B0 | ETN 1 | M12 |
| AGM12-8 | 9 | 145 | - | C53 | 150 | 90 | 95 | B0 | ETN 1 | M12 |
| AGM12-9 | 9 | 120 | - | C43 | 135 | 75 | 140 | B0 | ETN 1 | M04 |
| AGM12-10 | 10 | 150 | - | C55 | 150 | 90 | 130 | B0 | ETN 1 | M04 |
| AGM12-10.5 | 10 | 160 | - | C51 | 150 | 70 | 130 | B0 | ETN 1 | M04 |
| AGM12-11 | 11 | 205 | - | C74 | 150 | 90 | 110 | B0 | ETN 1 | M04 |
| AGM12-12 | 12 | 200 | - | C56 | 150 | 90 | 145 | B0 | ETN 1 | M04 |

| | Performance | | | Dimensions | | | | Technical characteristics | | |
|-------------|---------------|---------|----|------------|--------|--------|--------|---------------------------|----------|----------------|
| Part number | Capacity (Ah) | CCA (A) | WH | Box size | L (mm) | W (mm) | H (mm) | Hold Down | Polarity | Terminal Type |
| AGM12-12.1 | 12 | 200 | - | C56 | 150 | 90 | 145 | B0 | ETN 0 | M04 |
| AGM12-12F | 12 | 150 | - | C76 | 150 | 100 | 100 | B0 | ETN 3 | Faston S (4,8) |
| AGM12-12M | 12 | 200 | - | C56 | 150 | 90 | 145 | B0 | ETN 1 | M12 |
| AGM12-14 | 12 | 210 | - | C49 | 135 | 90 | 165 | B0 | ETN 0 | M04 |
| AGM12-14.1 | 12 | 210 | - | C49 | 135 | 90 | 165 | B0 | ETN 1 | M04 |
| AGM12-15 | 14 | 215 | - | C57 | 150 | 90 | 160 | B0 | ETN 1 | M04 |
| AGM12-16 | 16 | 200 | - | C57 | 150 | 90 | 160 | B0 | ETN 1 | M04 |
| AGM12-17 | 18 | 230 | - | C57 | 150 | 90 | 160 | B0 | ETN 1 | M04 |
| AGM12-18 | 18 | 250 | - | C64 | 180 | 75 | 165 | B0 | ETN 0 | M11 |
| AGM12-19 | 18 | 270 | - | C61 | 175 | 90 | 155 | B0 | ETN 0 | M04 |
| AGM12-19.1 | 18 | 270 | - | C61 | 175 | 90 | 155 | B0 | ETN 1 | M04 |
| AGM12-23 | 21 | 350 | - | C71 | 205 | 90 | 165 | B0 | ETN 0 | M04 |
| AGM12-31 | 30 | 430 | - | C52 | 165 | 130 | 175 | B0 | ETN 0 | M04 |

EXIDE AGM MC (Dry)

| | | | | | | | | | | |
|-------------|-----|-----|---|-----|-----|----|-----|----|-------|-----|
| ET4B-BS | 2.3 | 35 | - | C33 | 115 | 40 | 85 | B0 | ETN 4 | M13 |
| ETR4A-BS | 2.3 | 35 | - | C34 | 115 | 50 | 85 | B0 | ETN 4 | M14 |
| ETX4L-BS | 3 | 50 | - | C35 | 115 | 70 | 85 | B0 | ETN 0 | M04 |
| ETX5L-BS | 4 | 70 | - | C36 | 115 | 70 | 105 | B0 | ETN 0 | M04 |
| ETZ7-BS | 6 | 100 | - | C36 | 115 | 70 | 105 | B0 | ETN 0 | M04 |
| ETX7A-BS | 6 | 90 | - | C53 | 150 | 90 | 95 | B0 | ETN 1 | M04 |
| ETX7L-BS | 6 | 100 | - | C37 | 115 | 70 | 130 | B0 | ETN 0 | M04 |
| ET7B-BS | 6.5 | 85 | - | C50 | 150 | 65 | 95 | B0 | ETN 1 | M04 |
| ET9B-BS | 8 | 110 | - | C73 | 150 | 70 | 105 | B0 | ETN 1 | M04 |
| ETX9-BS | 8 | 120 | - | C54 | 150 | 90 | 105 | B0 | ETN 1 | M12 |
| ETZ10-BS | 8.6 | 145 | - | C53 | 150 | 90 | 95 | B0 | ETN 1 | M12 |
| ETX9C-BS | 9 | 120 | - | C43 | 135 | 75 | 140 | B0 | ETN 1 | M04 |
| ET12A-BS | 9.5 | 130 | - | C54 | 150 | 90 | 105 | B0 | ETN 1 | M04 |
| ET12B-BS | 10 | 160 | - | C51 | 150 | 70 | 130 | B0 | ETN 1 | M04 |
| ETX12-BS | 10 | 150 | - | C55 | 150 | 90 | 130 | B0 | ETN 1 | M04 |
| ETZ14-BS | 11 | 205 | - | C74 | 150 | 90 | 110 | B0 | ETN 1 | M04 |
| ETX14AH-BS | 12 | 210 | - | C49 | 135 | 90 | 165 | B0 | ETN 1 | M04 |
| ETX14AHL-BS | 12 | 210 | - | C49 | 135 | 90 | 165 | B0 | ETN 0 | M04 |
| ETX14-BS | 12 | 200 | - | C56 | 150 | 90 | 145 | B0 | ETN 1 | M04 |
| ETX14L-BS | 12 | 200 | - | C56 | 150 | 90 | 145 | B0 | ETN 0 | M04 |
| ET14B-BS | 12 | 190 | - | C75 | 150 | 70 | 145 | B0 | ETN 1 | M04 |
| ETX16-BS | 14 | 215 | - | C57 | 150 | 90 | 160 | B0 | ETN 1 | M04 |

| | Performance | | | Dimensions | | | | Technical characteristics | | |
|-------------|---------------|---------|----|------------|--------|--------|--------|---------------------------|----------|---------------|
| Part number | Capacity (Ah) | CCA (A) | WH | Box size | L (mm) | W (mm) | H (mm) | Hold Down | Polarity | Terminal Type |
| ETX20CH-BS | 18 | 230 | - | C57 | 150 | 90 | 160 | B0 | ETN 1 | M04 |
| ETX20H-BS | 18 | 270 | - | C61 | 175 | 90 | 155 | B0 | ETN 1 | M04 |
| ETX20HL-BS | 18 | 270 | - | C61 | 175 | 90 | 155 | B0 | ETN 0 | M04 |
| ETX24HL-BS | 21 | 350 | - | C71 | 205 | 90 | 165 | B0 | ETN 0 | M04 |

EXIDE Conventional

| | | | | | | | | | | |
|-------------|-----|-----|---|-----|-----|-----|-----|----|-------|-----|
| EB4L-B | 4 | 50 | - | C39 | 120 | 70 | 95 | B0 | ETN 0 | M04 |
| EB5L-B | 5 | 65 | - | C38 | 120 | 60 | 130 | B0 | ETN 0 | M06 |
| 12N5-3B | 5 | 40 | - | C38 | 120 | 60 | 130 | B0 | ETN 0 | M06 |
| 12N5,5-3B | 5.5 | 45 | - | C41 | 135 | 60 | 130 | B0 | ETN 0 | M06 |
| 6N6-3B-1 | 6 | 40 | - | C09 | 100 | 55 | 110 | B0 | ETN 2 | M06 |
| 12N7-3B | 7 | 75 | - | C42 | 135 | 75 | 135 | B0 | ETN 0 | M06 |
| EB7-A | 8 | 85 | - | C42 | 135 | 75 | 135 | B0 | ETN 1 | M06 |
| EB7L-B | 8 | 85 | - | C42 | 135 | 75 | 135 | B0 | ETN 0 | M06 |
| EB9-B | 9 | 100 | - | C43 | 135 | 75 | 140 | B0 | ETN 1 | M06 |
| 12N9-3B | 9 | 85 | - | C43 | 135 | 75 | 140 | B0 | ETN 0 | M06 |
| 12N9-4B-1 | 9 | 85 | - | C43 | 135 | 75 | 140 | B0 | ETN 1 | M06 |
| EB10L-B | 11 | 130 | - | C47 | 135 | 90 | 145 | B0 | ETN 0 | M06 |
| EB10L-B2 | 11 | 130 | - | C47 | 135 | 90 | 145 | B0 | ETN 0 | M08 |
| 6N11A-1B | 11 | 95 | - | C10 | 120 | 60 | 130 | B0 | ETN 0 | M06 |
| EB10L-A2 | 11 | 130 | - | C47 | 135 | 90 | 145 | B0 | ETN 0 | M08 |
| 12N12A-4A-1 | 12 | 115 | - | C45 | 135 | 80 | 160 | B0 | ETN 1 | M06 |
| EB12A-A | 12 | 165 | - | C45 | 135 | 80 | 160 | B0 | ETN 1 | M06 |
| EB12AL-A | 12 | 165 | - | C45 | 135 | 80 | 160 | B0 | ETN 0 | M06 |
| EB12AL-A2 | 12 | 165 | - | C45 | 135 | 80 | 160 | B0 | ETN 0 | M04 |
| 12N14-3A | 14 | 130 | - | C49 | 135 | 90 | 165 | B0 | ETN 0 | M08 |
| EB14-A2 | 14 | 145 | - | C49 | 135 | 90 | 165 | B0 | ETN 1 | M08 |
| EB14-B2 | 14 | 145 | - | C49 | 135 | 90 | 165 | B0 | ETN 1 | M08 |
| EB14L-A2 | 14 | 145 | - | C49 | 135 | 90 | 165 | B0 | ETN 0 | M08 |
| EB14L-B2 | 14 | 145 | - | C49 | 135 | 90 | 165 | B0 | ETN 0 | M08 |
| EB16AL-A2 | 16 | 175 | - | C70 | 205 | 70 | 165 | B0 | ETN 0 | M02 |
| EB18L-A | 18 | 190 | - | C65 | 180 | 90 | 160 | B0 | ETN 0 | M07 |
| EB16-B | 19 | 190 | - | C62 | 175 | 100 | 155 | B0 | ETN 1 | M06 |
| EB16CL-B | 19 | 190 | - | C63 | 175 | 100 | 175 | B0 | ETN 0 | M04 |
| EB16L-B | 19 | 190 | - | C62 | 175 | 100 | 155 | B0 | ETN 0 | M06 |
| E50-N18L-A | 20 | 260 | - | C71 | 205 | 90 | 165 | B0 | ETN 0 | M07 |
| E50-N18L-A3 | 20 | 260 | - | C71 | 205 | 90 | 165 | B0 | ETN 0 | M04 |

| | Performance | | | Dimensions | | | | Technical characteristics | | |
|-------------|---------------|---------|----|------------|--------|--------|--------|---------------------------|----------|---------------|
| Part number | Capacity (Ah) | CCA (A) | WH | Box size | L (mm) | W (mm) | H (mm) | Hold Down | Polarity | Terminal Type |
| 12Y16A-3A | 20 | 210 | - | C66 | 185 | 80 | 170 | B0 | ETN 0 | M11 |
| 12N24-3A | 24 | 220 | - | C67 | 185 | 125 | 175 | B0 | ETN 0 | M03 |
| U1-9 | 24 | 240 | - | C69 | 195 | 130 | 180 | B0 | ETN 1 | M11 |
| 12N24-4A | 24 | 220 | - | C67 | 185 | 125 | 175 | B0 | ETN 1 | M03 |
| E60-N24L-A | 28 | 280 | - | C67 | 185 | 125 | 175 | B0 | ETN 0 | M11 |
| U1R-11 | 30 | 300 | - | C69 | 195 | 130 | 180 | B0 | ETN 0 | M11 |
| E60-N30-A | 30 | 300 | - | C68 | 185 | 130 | 170 | B0 | ETN 1 | M11 |
| E60-N30L-A | 30 | 300 | - | C68 | 185 | 130 | 170 | B0 | ETN 0 | M11 |
| E60-N30L-B | 30 | 300 | - | C68 | 185 | 130 | 170 | B0 | ETN 0 | M11 |
| EB30L-B | 30 | 300 | - | C52 | 165 | 130 | 175 | B0 | ETN 0 | M04 |

EXIDE Garden

| | | | | | | | | | | |
|---------|----|-----|---|-----|-----|-----|-----|----|-------|-------------------|
| U1L-250 | 24 | 250 | - | U01 | 197 | 132 | 186 | B0 | ETN 1 | EN small Ford lug |
| U1R-250 | 24 | 250 | - | U01 | 197 | 132 | 186 | B0 | ETN 0 | EN small Ford lug |

Design, features and specifications are subject to change without notice. We disclaim any representation or warranty, express or implied, concerning the data or recommendations, and in no event shall be liable for any loss or damage claimed to have arisen as a result. Some products may not be available in your local market.